

Robin Cyclone - DMX chart

Version 1.1

Mode/Channel			Value	Function	Type of control
1	2	3			
1	1	1	0-255	Pan (8 bit) Pan movement by 450°	proportional
-	2	2	0-255	Pan Fine (16 bit) Fine control of pan movement	proportional
2	3	3	0-255	Tilt (8bit) Tilt movement by 300°	proportional
-	4	4	0-255	Tilt fine (16 bit) Fine control of tilt movement	proportional
3	5	5	0	Pan/Tilt speed, Pan/Tilt time Standard Mode	step
			1	Max. Speed mode	proportional
			2 - 255	Pan/Tilt speed Speed from max. to min.	proportional
			2 - 255	Pan/Tilt time Time from 0.2 s to 25.5 s.	proportional
4	6	6	0 - 9	Special functions Reserved <i>To activate following functions , stop in DMX value for at least 3sec. and shutter must be closed at least 3sec. (Shutter channel 15/22 must be at range of 0-31DMX). Corresponding menu items are temporarily overrided except DMX Input.</i>	
			10 - 14	DMX input: Wired DMX *	step
			15 - 19	DMX input: Wireless DMX* * function is active only 10 seconds after switching the fixture on	step
			20 - 49	Reserved	
			50 - 59	Pan/Tilt speed mode	step
			60 - 69	Pan/Tilt time mode	step
			70 - 79	Blackout while pan/tilt moving	step
			80 - 89	Disabled blackout while pan/tilt moving	step
			90 - 139	Reserved <i>To activate following reset function, stop in DMX value for at least 3 sec.</i>	
			140 - 149	Pan/Tilt reset	step
			150 - 179	Reserved	
			180 - 189	Zoom reset	step
			190 - 199	Reserved	
200 - 209	Total reset	step			
210 - 255	Reserved				
5	7	7	0	Fan speed Rotation=off	step
			1-255	Fan speed min.->max..	proportional
6	8	8	0-255	Red (8 bit) - all pixels Red LEDs saturation control (0-100%)	proportional
-	9	9	0-255	Red fine(16 bit) - all pixels Fine red LEDs saturation control	proportional
7	10	10	0-255	Green (8 bit) - all pixels Green LEDs saturation control (0-100%)	proportional
-	11	11	0-255	Green fine (16 bit) - all pixels Fine green LEDs saturation control	proportional
8	12	12	0-255	Blue (8 bit) - all pixels Blue LEDs saturation control (0-100%)	proportional
-	13	13	0-255	Blue fine (16 bit) - all pixels Fine blue LEDs saturation control	proportional

Mode/Channel			Value	Function	Type of control
1	2	3			
9	14	14	0-255	White (8 bit) - all pixels White LEDs saturation control (0-100%)	proportional
-	15	15	0-255	White fine (16 bit) - pixels Fine white LEDs saturation control	proportional
10	16	16	0 1-255	CTO No function Colour temperature correction from 15500K to 2700K	step proportional
11	17	17	0 1-2 3 4-5 6 7-9 10-12 13-15 16 17-55 56 57 - 95 96 97 - 134 135 136 - 174 175 176 -214 215 216 - 246 247 248-251 252-255	Virtual Colour Wheel For detailed description see " Virtual colour wheel- colour mixing chart No function White 2700 K White 2700 K (tungsten emulation**) White 3200 K White 3200 K (tungsten emulation**) White 4200 K White 5600 K White 8000 K Blue (Blue=full, Red+Green+White=0) Red=0, Green->up,Blue =full, White=0 Light Blue (Red=0, Green=full, Blue =full, White=0) Red=0, Green=full, Blue->down, White=0 Green (Red=0, Green=full, Blue =0, White=0) Red->up, Green=full, Blue=0, White=0 Yellow (Red=full, Green=full, Blue=0, White=0) Red=full, Green->down, Blue=0, White=0 Red(Red=full, Green=0, Blue=0, White=0) Red=full, Green=0, Blue->up, White=0 Magenta (Red=full, Green=0, Blue=full, White=0) Red -> down, Green=0, Blue=full, White=0 Blue (Red=0, Green=0, Blue=full, White=0) Rainbow effect(with fade time) from min.->max. speed Rainbow effect (without fade time) from min.->max.	step step step step step step step step step step proportional step proportional step proportional step proportional step proportional step proportional step proportional step proportional proportional
12	18	18		Pixel effects <i>See table below</i>	
13	19	19	0-63 64-127 128-191 192-255	Pixel effects speed Speed from min. —>max. without fade time Speed from max. —>min. without fade time (op. direc.) Speed from min. —>max. with fade time Speed from max. —>min. with fade time (op. direc.)	proportional proportional proportional proportional
14	20	20	0 - 255	Zoom (8 bit) Zoom from min. to max. beam angle	proportional proportional
-	21	21	0 - 255	Zoom fine (16 bit) Fine zooming from min. to max.	proportional
15	22	22	0-31 32-63 64-95 96-127 128-143 144-159 160-191 192-223 224-255	Shutter/Strobe Shutter closed Shutter open Strobe effect from slow--> fast Shutter open Opening pulses in sequences from slow--> fast Closing pulses in sequences from fast--> slow Shutter open Random strobe effect from slow--> fast Shutter open	step step proportional step proportional proportional step proportional step

Mode/Channel			Value	Function	Type of control
1	2	3			
16	23	23	0-255	Dimmer (8 bit) Dimmer intensity from 0% to 100%	proportional
-	24	24	0-255	Dimmer fine (16 bit) Fine dimming	proportional
-	-	25	0-255	Red pixel 1 Red LEDs saturation control (0-100%)	proportional
-	-	26	0-255	Green pixel 1 Green LEDs saturation control (0-100%)	proportional
-	-	27	0-255	Blue pixel 1 Blue LEDs saturation control (0-100%)	proportional
-	-	28	0-255	Red pixel 2 Red LEDs saturation control (0-100%)	proportional
-	-	29	0-255	Green pixel 2 Green LEDs saturation control (0-100%)	proportional
-	-	30	0-255	Blue pixel 2 Blue LEDs saturation control (0-100%)	proportional
-	-	31	0-255	Red pixel 3 Red LEDs saturation control (0-100%)	proportional
-	-	32	0-255	Green pixel 3 Green LEDs saturation control (0-100%)	proportional
-	-	33	0-255	Blue pixel 3 Blue LEDs saturation control (0-100%)	proportional
-	-	34	0-255	Red pixel 4 Red LEDs saturation control (0-100%)	proportional
-	-	35	0-255	Green pixel 4 Green LEDs saturation control (0-100%)	proportional
-	-	36	0-255	Blue pixel 4 Blue LEDs saturation control (0-100%)	proportional
-	-	37	0-255	Red pixel 5 Red LEDs saturation control (0-100%)	proportional
-	-	38	0-255	Green pixel 5 Green LEDs saturation control (0-100%)	proportional
-	-	39	0-255	Blue pixel 5 Blue LEDs saturation control (0-100%)	proportional
-	-	40	0-255	Red pixel 6 Red LEDs saturation control (0-100%)	proportional
-	-	41	0-255	Green pixel 6 Green LEDs saturation control (0-100%)	proportional
-	-	42	0-255	Blue pixel 6 Blue LEDs saturation control (0-100%)	proportional
-	-	43	0-255	Red pixel 7 Red LEDs saturation control (0-100%)	proportional
-	-	44	0-255	Green pixel 7 Green LEDs saturation control (0-100%)	proportional
-	-	45	0-255	Blue pixel 7 Blue LEDs saturation control (0-100%)	proportional
-	-	46	0-255	Red pixel 8 Red LEDs saturation control (0-100%)	proportional
-	-	47	0-255	Green pixel 8 Green LEDs saturation control (0-100%)	proportional
-	-	48	0-255	Blue pixel 8 Blue LEDs saturation control (0-100%)	proportional

Mode/Channel			Value	Function	Type of control
1	2	3			
-	-	49	0-255	Red pixel 9 Red LEDs saturation control (0-100%)	proportional
-	-	50	0-255	Green pixel 9 Green LEDs saturation control (0-100%)	proportional
-	-	51	0-255	Blue pixel 9 Blue LEDs saturation control (0-100%)	proportional
-	-	52	0-255	Red pixel 10 Red LEDs saturation control (0-100%)	proportional
-	-	53	0-255	Green pixel 10 Green LEDs saturation control (0-100%)	proportional
-	-	54	0-255	Blue pixel 10 Blue LEDs saturation control (0-100%)	proportional
-	-	55	0-255	Red pixel 11 Red LEDs saturation control (0-100%)	proportional
-	-	56	0-255	Green pixel 11 Green LEDs saturation control (0-100%)	proportional
-	-	57	0-255	Blue pixel 11 Blue LEDs saturation control (0-100%)	proportional
-	-	58	0-255	Red pixel 12 Red LEDs saturation control (0-100%)	proportional
-	-	59	0-255	Green pixel 12 Green LEDs saturation control (0-100%)	proportional
-	-	60	0-255	Blue pixel 12 Blue LEDs saturation control (0-100%)	proportional
-	-	61	0-255	Red pixel 13 Red LEDs saturation control (0-100%)	proportional
-	-	62	0-255	Green pixel 13 Green LEDs saturation control (0-100%)	proportional
-	-	63	0-255	Blue pixel 13 Blue LEDs saturation control (0-100%)	proportional
-	-	64	0-255	Red pixel 14 Red LEDs saturation control (0-100%)	proportional
-	-	65	0-255	Green pixel 14 Green LEDs saturation control (0-100%)	proportional
-	-	66	0-255	Blue pixel 14 Blue LEDs saturation control (0-100%)	proportional
-	-	67	0-255	Red pixel 15 Red LEDs saturation control (0-100%)	proportional
-	-	68	0-255	Green pixel 15 Green LEDs saturation control (0-100%)	proportional
-	-	69	0-255	Blue pixel 15 Blue LEDs saturation control (0-100%)	proportional
-	-	70	0-255	Red pixel 16 Red LEDs saturation control (0-100%)	proportional
-	-	71	0-255	Green pixel 16 Green LEDs saturation control (0-100%)	proportional
-	-	72	0-255	Blue pixel 16 Blue LEDs saturation control (0-100%)	proportional
-	-	73	0-255	Red pixel 17 Red LEDs saturation control (0-100%)	proportional
-	-	74	0-255	Green pixel 17 Green LEDs saturation control (0-100%)	proportional

Mode/Channel			Value	Function	Type of control
1	2	3			
-	-	75	0-255	Blue pixel 17 Blue LEDs saturation control (0-100%)	proportional
-	-	76	0-255	Red pixel 18 Red LEDs saturation control (0-100%)	proportional
-	-	77	0-255	Green pixel 18 Green LEDs saturation control (0-100%)	proportional
-	-	78	0-255	Blue pixel 18 Blue LEDs saturation control (0-100%)	proportional
-	-	79	0-255	Red pixel 19 Red LEDs saturation control (0-100%)	proportional
-	-	80	0-255	Green pixel 19 Green LEDs saturation control (0-100%)	proportional
-	-	81	0-255	Blue pixel 19 Blue LEDs saturation control (0-100%)	proportional
-	-	82	0-255	Red pixel 20 Red LEDs saturation control (0-100%)	proportional
-	-	83	0-255	Green pixel 20 Green LEDs saturation control (0-100%)	proportional
-	-	84	0-255	Blue pixel 20 Blue LEDs saturation control (0-100%)	proportional
-	-	85	0-255	Red pixel 21 Red LEDs saturation control (0-100%)	proportional
-	-	86	0-255	Green pixel 21 Green LEDs saturation control (0-100%)	proportional
-	-	87	0-255	Blue pixel 21 Blue LEDs saturation control (0-100%)	proportional
-	-	88	0-255	Red pixel 22 Red LEDs saturation control (0-100%)	proportional
-	-	89	0-255	Green pixel 22 Green LEDs saturation control (0-100%)	proportional
-	-	90	0-255	Blue pixel 22 Blue LEDs saturation control (0-100%)	proportional
-	-	91	0-255	Red pixel 23 Red LEDs saturation control (0-100%)	proportional
-	-	92	0-255	Green pixel 23 Green LEDs saturation control (0-100%)	proportional
-	-	93	0-255	Blue pixel 23 Blue LEDs saturation control (0-100%)	proportional
-	-	94	0-255	Red pixel 24 Red LEDs saturation control (0-100%)	proportional
-	-	95	0-255	Green pixel 24 Green LEDs saturation control (0-100%)	proportional
-	-	96	0-255	Blue pixel 24 Blue LEDs saturation control (0-100%)	proportional

**In the Halogen lamp mode the Dimmer channel imitates behaviour of the halogen lamp during dimming.

Channel "Pixel effects"

DMX value	Effect	Type of control
0-2	No function	Step
3-4	Effect 1	Step
5-6	Effect 2	Step
7-8	Effect 3	Step
9-10	Effect 4	Step
11-12	Effect 5	Step
13-14	Effect 6	Step
15-16	Effect 7	Step
17-18	Effect 8	Step
19-20	Effect 9	Step
21-22	Effect 10	Step
23-24	Effect 11	Step
25-26	Effect 12	Step
27-28	Effect 13	Step
29-30	Effect 14	Step
31-32	Effect 15	Step
33-34	Effect 16	Step
35-36	Effect 17	Step
37-38	Effect 18	Step
39-40	Effect 19	Step
41-42	Effect 20	Step
43-44	Effect 21	Step
45-46	Effect 22	Step
47-48	Effect 23	Step
49-50	Effect 24	Step
51-52	Effect 25	Step
53-54	Effect 26	Step
55-56	Effect 27	Step
57-58	Effect 28	Step
59-60	Effect 29	Step
61-62	Effect 30	Step
63-64	Effect 31	Step
65-66	Effect 32	Step
67-68	Effect 33	Step
69-70	Effect 34	Step
71-72	Effect 35	Step
73-74	Effect 36	Step
75-76	Effect 37	Step
77-78	Effect 38	Step
79-80	Effect 39	Step
81-82	Effect 40	Step
83-84	Effect 41	Step
85-86	Effect 42	Step
87-88	Effect 43	Step
89-90	Effect 44	Step
91-92	Effect 45	Step
93-94	Effect 46	Step

Channel "Pixel effects"

DMX value	Effect	Type of control
95-96	Effect 47	Step
97-98	Effect 48	Step
99-100	Effect 49	Step
101-102	Effect 50	Step
103-104	Effect 51	Step
105-106	Effect 52	Step
107-108	Effect 53	Step
109-110	Effect 54	Step
111-112	Effect 55	Step
113-114	Effect 56	Step
115-116	Effect 57	Step
117-118	Effect 58	Step
119-120	Effect 59	Step
121-122	Effect 60	Step
123-124	Effect 61	Step
125-126	Effect 62	Step
127-128	Effect 63	Step
129-130	Effect 64	Step
131-132	Effect 65	Step
133-134	Effect 66	Step
135-136	Effect 67	Step
137-138	Effect 68	Step
139-140	Effect 69	Step
141-142	Effect 70	Step
143-144	Effect 71	Step
145-146	Effect 72	Step
147-148	Effect 73	Step
149-150	Effect 74	Step
151-152	Effect 75	Step
153-154	Effect 76	Step
155-156	Effect 77	Step
157-158	Effect 78	Step
159-160	Effect 79	Step
161-162	Effect 80	Step
163-164	Effect 81	Step
165-166	Effect 82	Step
167-168	Effect 83	Step
169-170	Effect 84	Step
171-172	Effect 85	Step
173-174	Effect 86	Step
175-176	Effect 87	Step
177-178	Effect 88	Step
179-255	Reserved	

Virtual colour wheel					
Scale*	Virtual Colour Wheel	Red	Green	Blue	White
	DMX	DMX	DMX	DMX	DMX
	1-2 (White 2700K)	255	119	0	57
	3 (White 2700K /Hal.mode/)	255	119	0	57
	4-5 (White 3200K)	255	128	0	100
	6 (White 3200K /Hal.mode/)	255	128	0	100
	7-9 (White 4200K)	255	143	4	218
	10-12 (White 5600K)	255	206	31	255
	13-15 (White 8000K)	217	255	71	255
	16	0	0	255	0
	17	0	3	255	0
	18	0	6	255	0
	19	0	9	255	0
	20	0	12	255	0
	21	0	15	255	0
	22	0	18	255	0
	23	0	21	255	0
	24	0	24	255	0
	25	0	27	255	0
	26	0	30	255	0
	27	0	36	255	0
	28	0	41	255	0
	29	0	46	255	0
	30	0	52	255	0
	31	0	58	255	0
	32	0	64	255	0
	33	0	68	255	0
	34	0	74	255	0
	35	0	80	255	0
	36	0	86	255	0
	37	0	92	255	0
	38	0	98	255	0
	39	0	104	255	0
	40	0	110	255	0
	41	0	119	255	0
	42	0	129	255	0
	43	0	138	255	0
	44	0	147	255	0
	45	0	156	255	0
	46	0	165	255	0
	47	0	174	255	0
	48	0	183	255	0
	49	0	192	255	0
	50	0	201	255	0
	51	0	210	255	0
	52	0	219	255	0
	53	0	228	255	0
	54	0	237	255	0
	55	0	246	255	0
	56	0	255	255	0
	57	0	255	246	0
	58	0	255	237	0
	59	0	255	228	0
	60	0	255	219	0
	61	0	255	210	0
	62	0	255	201	0
	63	0	255	192	0

Scale*	Virtual Colour Wheel	Red	Green	Blue	White
	DMX	DMX	DMX	DMX	DMX
	64	0	255	183	0
	65	0	255	174	0
	66	0	255	165	0
	67	0	255	156	0
	68	0	255	147	0
	69	0	255	138	0
	70	0	255	129	0
	71	0	255	119	0
	72	0	255	110	0
	73	0	255	104	0
	74	0	255	98	0
	75	0	255	92	0
	76	0	255	86	0
	77	0	255	80	0
	78	0	255	74	0
	79	0	255	68	0
	80	0	255	64	0
	81	0	255	58	0
	82	0	255	52	0
	83	0	255	46	0
	84	0	255	41	0
	82	0	255	36	0
	86	0	255	30	0
	87	0	255	27	0
	88	0	255	24	0
	89	0	255	21	0
	90	0	255	18	0
	91	0	255	15	0
	92	0	255	12	0
	93	0	255	9	0
	94	0	255	6	0
	95	0	255	3	0
	96	0	255	0	0
	97	3	255	0	0
	98	6	255	0	0
	99	9	255	0	0
	100	12	255	0	0
	101	15	255	0	0
	102	18	255	0	0
	103	21	255	0	0
	104	24	255	0	0
	105	27	255	0	0
	106	30	255	0	0
	107	36	255	0	0
	108	41	255	0	0
	109	46	255	0	0
	110	52	255	0	0
	111	58	255	0	0
	112	64	255	0	0
	113	68	255	0	0
	114	74	255	0	0
	115	80	255	0	0
	116	86	255	0	0
	117	92	255	0	0
	118	98	255	0	0

Scale*	Virtual Colour Wheel	Red	Green	Blue	White
	DMX	DMX	DMX	DMX	DMX
	119	104	255	0	0
	120	110	255	0	0
	121	119	255	0	0
	122	129	255	0	0
	123	138	255	0	0
	124	147	255	0	0
	125	156	255	0	0
	126	165	255	0	0
	127	174	255	0	0
	128	183	255	0	0
	129	192	255	0	0
	130	201	255	0	0
	131	210	255	0	0
	132	219	255	0	0
	133	228	255	0	0
	134	240	255	0	0
	135	255	255	0	0
	136	255	246	0	0
	137	255	237	0	0
	138	255	228	0	0
	139	255	219	0	0
	140	255	210	0	0
	141	255	201	0	0
	142	255	192	0	0
	143	255	183	0	0
	144	255	174	0	0
	145	255	165	0	0
	146	255	156	0	0
	147	255	147	0	0
	148	255	138	0	0
	149	255	129	0	0
	150	255	119	0	0
	151	255	110	0	0
	152	255	104	0	0
	153	255	98	0	0
	154	255	92	0	0
	155	255	86	0	0
	156	255	80	0	0
	157	255	74	0	0
	158	255	68	0	0
	159	255	64	0	0
	160	255	58	0	0
	161	255	52	0	0
	162	255	46	0	0
	163	255	41	0	0
	164	255	36	0	0
	165	255	30	0	0
	166	255	27	0	0
	167	255	24	0	0
	168	255	21	0	0
	169	255	18	0	0
	170	255	15	0	0
	171	255	12	0	0
	172	255	9	0	0
	173	255	6	0	0

Scale*	Virtual Colour Wheel	Red	Green	Blue	White
	DMX	DMX	DMX	DMX	DMX
	174	255	3	0	0
	175	255	0	0	0
	176	255	0	3	0
	177	255	0	6	0
	178	255	0	9	0
	179	255	0	12	0
	180	255	0	15	0
	181	255	0	18	0
	182	255	0	21	0
	183	255	0	24	0
	184	255	0	27	0
	185	255	0	30	0
	186	255	0	36	0
	187	255	0	41	0
	188	255	0	46	0
	189	255	0	52	0
	190	255	0	58	0
	191	255	0	64	0
	192	255	0	68	0
	193	255	0	74	0
	194	255	0	80	0
	195	255	0	86	0
	196	255	0	92	0
	197	255	0	98	0
	198	255	0	104	0
	199	255	0	110	0
	200	255	0	119	0
	201	255	0	129	0
	202	255	0	138	0
	203	255	0	147	0
	204	255	0	156	0
	205	255	0	165	0
	206	255	0	174	0
	207	255	0	183	0
	208	255	0	192	0
	209	255	0	201	0
	210	255	0	210	0
	211	255	0	219	0
	212	255	0	228	0
	213	255	0	237	0
	214	255	0	246	0
	215	255	0	255	0
	216	246	0	255	0
	217	237	0	255	0
	218	228	0	255	0
	219	219	0	255	0
	220	210	0	255	0
	221	201	0	255	0
	222	192	0	255	0
	223	183	0	255	0
	224	174	0	255	0
	225	165	0	255	0
	226	156	0	255	0
	227	147	0	255	0
	228	138	0	255	0

Scale*	Virtual Colour Wheel	Red	Green	Blue	White
	DMX	DMX	DMX	DMX	DMX
	229	129	0	255	0
	230	119	0	255	0
	231	110	0	255	0
	232	104	0	255	0
	233	98	0	255	0
	234	91	0	255	0
	235	84	0	255	0
	236	77	0	255	0
	237	70	0	255	0
	238	63	0	255	0
	239	56	0	255	0
	240	49	0	255	0
	241	42	0	255	0
	242	35	0	255	0
	243	28	0	255	0
	244	21	0	255	0
	245	14	0	255	0
	246	7	0	255	0
	247	0	0	255	0
	248-255 (Rainbow+ zone effects)	****	****	****	****
* Colour scale as an illustration only					