

## Robin ParFect 100 - DMX chart

Version 1.4    **Mode 1 - Standard 16 bit, Mode 2 - Reduced 8bit, Mode 3 - Basic,  
Mode 4 - Extended 16bit, Mode 5 - Robin 100 LedBeam compatible, Mode 6 - RGBW, Mode 7 - RGBWSD**

Mode/Channel							Value	Function	Type of control
1	2	3	4	5	6	7			
-	-	-	-	1	-	-		No function	
-	-	-	-	2	-	-		No function	
-	-	-	-	3	-	-		No function	
-	-	-	-	4	-	-		No function	
-	-	-	-	5	-	-		No function	
1	1	1	1	6	-	-	0 - 29	<b>Special functions</b> Reserved <i>To activate following functions (30-129DMX), stop in DMX value for at least 3sec. and shutter must be closed at least 3sec. (Shutter channel 12/8/3/28/33 must be at range of 0-31DMX). Corresponding menu items are temporarily overridden.</i>	step
							30 - 39	RGBW colour mixing mode	step
							40 - 49	CMY colour mixing mode	step
							50-109	Reserved	
							110-114	Colour calibration mode On	step
							115-119	Colour calibration mode Off	step
							120-124	Audio control On	step
125-129	Audio control Off	step							
130-145	Effect speed control, slow--> fast	proportional							
146-161	Effect speed control, fast--> slow /opposite direction/	proportional							
162-255	Reserved								
2	2	-	-	-	1	1	0-255	<b>Red/Cyan (8 bit) - all zones</b> Red LEDs saturation control (0-100%)	proportional
3	-	-	-	-	-	-	0-255	<b>Red/Cyan fine(16 bit) - all zones</b> Fine red LEDs saturation control	proportional
4	3	-	-	-	2	2	0-255	<b>Green/Magenta (8 bit) - all zones</b> Green LEDs saturation control (0-100%)	proportional
5	-	-	-	-	-	-	0-255	<b>Green/Magenta fine (16 bit) - all zones</b> Fine green LEDs saturation control	proportional
6	4	-	-	-	3	3	0-255	<b>Blue/Yellow (8 bit) - all zones</b> Blue LEDs saturation control (0-100%)	proportional
7	-	-	-	-	-	-	0-255	<b>Blue/Yellow fine (16 bit) - all zones</b> Fine blue LEDs saturation control	proportional
8	5	-	-	-	4	4	0-255	<b>White (8 bit) - all zones</b> <i>If RGBW mode is selected:</i> White colour saturation control coarse (0-100%) <i>If CMY mode is selected:</i> No function	proportional
9	-	-	-	-	-	-	0-255	<b>White fine (16 bit) - all zones</b> Fine white LEDs saturation control (RGBW mode)	proportional
-	-	-	2	7	-	-	0-255	<b>Red/Cyan (8 bit) - zone 1</b> Red LEDs saturation control (0-100%)	proportional
-	-	-	3	8	-	-	0-255	<b>Red/Cyan fine (16 bit) - zone 1</b> Fine red LEDs saturation control	proportional
-	-	-	4	9	-	-	0-255	<b>Green/Magenta (8 bit) - zone 1</b> Green LEDs saturation control (0-100%)	proportional
-	-	-	5	10	-	-	0-255	<b>Green/Magenta fine (16 bit) - zone 1</b> Fine green LEDs saturation control	proportional

Mode/Channel							Value	Function	Type of control
1	2	3	4	5	6	7			
-	-	-	6	11	-	-	0-255	<b>Blue/Yellow (8 bit) zone 1</b> Blue LEDs saturation control (0-100%)	proportional
-	-	-	7	12	-	-	0-255	<b>Blue/Yellow (16 bit) zone 1</b> Fine blue LEDs saturation control)	proportional
-	-	-	8	13	-	-	0-255	<b>White (8 bit) - zone 1</b> <i>If RGBW mode is selected:</i> White colour saturation control coarse (0-100%) <i>If CMY mode is selected:</i> No function	proportional
-	-	-	9	14	-	-	0-255	<b>White (16 bit) - zone 1</b> Fine white LEDs saturation control (RGBW mode)	proportional
-	-	-	10	15	-	-	0-255	<b>Red/Cyan (8bit) - zone 2</b> Red LEDs saturation control (0-100%)	proportional
-	-	-	11	16	-	-	0-255	<b>Red/Cyan fine (16 bit) - zone 2</b> Fine red LEDs saturation control	proportional
-	-	-	12	17	-	-	0-255	<b>Green/Magenta (8 bit) - zone 2</b> Green LEDs saturation control (0-100%)	proportional
-	-	-	13	18	-	-	0-255	<b>Green/Magenta fine (16 bit) - zone 2</b> Fine green LEDs saturation control	proportional
-	-	-	14	19	-	-	0-255	<b>Blue/Yellow (8 bit) - zone 2</b> Blue LEDs saturation control (0-100%)	proportional
-	-	-	15	20	-	-	0-255	<b>Blue/Yellow fine (16 bit) - zone 2</b> Fine blue LEDs saturation control	proportional
-	-	-	16	21	-	-	0-255	<b>White (8 bit) - zone 2</b> <i>If RGBW mode is selected:</i> White colour saturation control coarse (0-100%) <i>If CMY mode is selected:</i> No function	proportional
-	-	-	17	22	-	-	0-255	<b>White (16 bit) - zone 2</b> Fine white LEDs saturation control (RGBW mode)	proportional
-	-	-	18	23	-	-	0-255	<b>Red/Cyan (8 bit) - zone 3</b> Red LEDs saturation control (0-100%)	proportional
-	-	-	19	24	-	-	0-255	<b>Red/ Cyan fine (16 bit) - zone 3</b> Fine red LEDs saturation control	proportional
-	-	-	20	25	-	-	0-255	<b>Green/Magenta (8 bit) - zone 3</b> Green LEDs saturation control (0-100%)	proportional
-	-	-	21	26	-	-	0-255	<b>Green/Magenta fine (16 bit) - zone 3</b> Fine green LEDs saturation control	proportional
-	-	-	22	27	-	-	0-255	<b>Blue/Yellow (8 bit) zone 3</b> Blue LEDs saturation control (0-100%)	proportional
-	-	-	23	28	-	-	0-255	<b>Blue/Yellow fine (16 bit) zone 3</b> Fine blue LEDs saturation control	proportional
-	-	-	24	29	-	-	0-255	<b>White (8 bit) zone 3</b> <i>If RGBW mode is selected:</i> White colour saturation control coarse (0-100%) <i>If CMY mode is selected:</i> No function	proportional
-	-	-	25	30	-	-	0-255	<b>White fine (16 bit) zone 3</b> Fine white LEDs saturation control (RGBW mode)	proportional
10	6	-	26	31	-	-	0 1-255	<b>CTC</b> No function Colour temperature correction from 19000K to 2700K	step proportional



## Virtual colour wheel - colour mixing chart

Scale*	Virtual Colour Wheel	Red	Green	Blue	White
	DMX	DMX	DMX	DMX	DMX
	1-2 (White 2700K)	250	118	0	63
	3 (White 2700K /Hal.mode/)	250	118	0	63
	4-5 (White 3200K)	255	141	5	89
	6 (White 3200K /Hal.mode/)	255	141	5	89
	7-9 (White 4200K)	254	141	3	255
	10-12 (White 5600K)	254	207	37	255
	13-15 (White 8000K)	228	255	79	255
	16	0	0	255	0
	17	0	3	255	0
	18	0	6	255	0
	19	0	9	255	0
	20	0	12	255	0
	21	0	15	255	0
	22	0	18	255	0
	23	0	21	255	0
	24	0	24	255	0
	25	0	27	255	0
	26	0	30	255	0
	27	0	36	255	0
	28	0	41	255	0
	29	0	46	255	0
	30	0	52	255	0
	31	0	58	255	0
	32	0	64	255	0
	33	0	68	255	0
	34	0	74	255	0
	35	0	80	255	0
	36	0	86	255	0
	37	0	92	255	0
	38	0	98	255	0
	39	0	104	255	0
	40	0	110	255	0
	41	0	119	255	0
	42	0	129	255	0
	43	0	138	255	0
	44	0	147	255	0
	45	0	156	255	0
	46	0	165	255	0
	47	0	174	255	0
	48	0	183	255	0
	49	0	192	255	0
	50	0	201	255	0
	51	0	210	255	0
	52	0	219	255	0
	53	0	228	255	0
	54	0	237	255	0
	55	0	246	255	0
	56	0	255	255	0
	57	0	255	246	0
	58	0	255	237	0
	59	0	255	228	0
	60	0	255	219	0
	61	0	255	210	0
	62	0	255	201	0
	63	0	255	192	0

Scale*	Virtual Colour Wheel	Red	Green	Blue	White
	DMX	DMX	DMX	DMX	DMX
	64	0	255	183	0
	65	0	255	174	0
	66	0	255	165	0
	67	0	255	156	0
	68	0	255	147	0
	69	0	255	138	0
	70	0	255	129	0
	71	0	255	119	0
	72	0	255	110	0
	73	0	255	104	0
	74	0	255	98	0
	75	0	255	92	0
	76	0	255	86	0
	77	0	255	80	0
	78	0	255	74	0
	79	0	255	68	0
	80	0	255	64	0
	81	0	255	58	0
	82	0	255	52	0
	83	0	255	46	0
	84	0	255	41	0
	82	0	255	36	0
	86	0	255	30	0
	87	0	255	27	0
	88	0	255	24	0
	89	0	255	21	0
	90	0	255	18	0
	91	0	255	15	0
	92	0	255	12	0
	93	0	255	9	0
	94	0	255	6	0
	95	0	255	3	0
	96	0	255	0	0
	97	3	255	0	0
	98	6	255	0	0
	99	9	255	0	0
	100	12	255	0	0
	101	15	255	0	0
	102	18	255	0	0
	103	21	255	0	0
	104	24	255	0	0
	105	27	255	0	0
	106	30	255	0	0
	107	36	255	0	0
	108	41	255	0	0
	109	46	255	0	0
	110	52	255	0	0
	111	58	255	0	0
	112	64	255	0	0
	113	68	255	0	0
	114	74	255	0	0
	115	80	255	0	0
	116	86	255	0	0
	117	92	255	0	0
	118	98	255	0	0

Scale*	Virtual Colour Wheel	Red	Green	Blue	White
	DMX	DMX	DMX	DMX	DMX
	119	104	255	0	0
	120	110	255	0	0
	121	119	255	0	0
	122	129	255	0	0
	123	138	255	0	0
	124	147	255	0	0
	125	156	255	0	0
	126	165	255	0	0
	127	174	255	0	0
	128	183	255	0	0
	129	192	255	0	0
	130	201	255	0	0
	131	210	255	0	0
	132	219	255	0	0
	133	228	255	0	0
	134	240	255	0	0
	135	255	255	0	0
	136	255	246	0	0
	137	255	237	0	0
	138	255	228	0	0
	139	255	219	0	0
	140	255	210	0	0
	141	255	201	0	0
	142	255	192	0	0
	143	255	183	0	0
	144	255	174	0	0
	145	255	165	0	0
	146	255	156	0	0
	147	255	147	0	0
	148	255	138	0	0
	149	255	129	0	0
	150	255	119	0	0
	151	255	110	0	0
	152	255	104	0	0
	153	255	98	0	0
	154	255	92	0	0
	155	255	86	0	0
	156	255	80	0	0
	157	255	74	0	0
	158	255	68	0	0
	159	255	64	0	0
	160	255	58	0	0
	161	255	52	0	0
	162	255	46	0	0
	163	255	41	0	0
	164	255	36	0	0
	165	255	30	0	0
	166	255	27	0	0
	167	255	24	0	0
	168	255	21	0	0
	169	255	18	0	0
	170	255	15	0	0
	171	255	12	0	0
	172	255	9	0	0
	173	255	6	0	0

Scale*	Virtual Colour Wheel	Red	Green	Blue	White
	DMX	DMX	DMX	DMX	DMX
	174	255	3	0	0
	175	255	0	0	0
	176	255	0	3	0
	177	255	0	6	0
	178	255	0	9	0
	179	255	0	12	0
	180	255	0	15	0
	181	255	0	18	0
	182	255	0	21	0
	183	255	0	24	0
	184	255	0	27	0
	185	255	0	30	0
	186	255	0	36	0
	187	255	0	41	0
	188	255	0	46	0
	189	255	0	52	0
	190	255	0	58	0
	191	255	0	64	0
	192	255	0	68	0
	193	255	0	74	0
	194	255	0	80	0
	195	255	0	86	0
	196	255	0	92	0
	197	255	0	98	0
	198	255	0	104	0
	199	255	0	110	0
	200	255	0	119	0
	201	255	0	129	0
	202	255	0	138	0
	203	255	0	147	0
	204	255	0	156	0
	205	255	0	165	0
	206	255	0	174	0
	207	255	0	183	0
	208	255	0	192	0
	209	255	0	201	0
	210	255	0	210	0
	211	255	0	219	0
	212	255	0	228	0
	213	255	0	237	0
	214	255	0	246	0
	215	255	0	255	0
	216	246	0	255	0
	217	237	0	255	0
	218	228	0	255	0
	219	219	0	255	0
	220	210	0	255	0
	221	201	0	255	0
	222	192	0	255	0
	223	183	0	255	0
	224	174	0	255	0
	225	165	0	255	0
	226	156	0	255	0
	227	147	0	255	0
	228	138	0	255	0

Scale*	Virtual Colour Wheel	Red	Green	Blue	White
	DMX	DMX	DMX	DMX	DMX
	229	129	0	255	0
	230	119	0	255	0
	231	110	0	255	0
	232	104	0	255	0
	233	98	0	255	0
	234	91	0	255	0
	235	84	0	255	0
	236	77	0	255	0
	237	70	0	255	0
	238	63	0	255	0
	239	56	0	255	0
	240	49	0	255	0
	241	42	0	255	0
	242	35	0	255	0
	243	28	0	255	0
	244	21	0	255	0
	245	14	0	255	0
	246	7	0	255	0
	247	0	0	255	0
	248-255 (Rainbow+ zone effects)	****	****	****	****

\* Colour scale as an illustration only

### LED zone order

